

SOGEVAC®

SV25 FP

Single-stage, oil-sealed rotary vane pump

Original Operating Instructions 300419811_002_C2 and spare parts list

Ref: 960251FP 960256FP 960257FP 960261FP



Contents

0	Important Safety Information	4
1	Description	6
1.1	Principle of operation	6
1.2	Standard specification	6
1.3	Technical characteristics	7
1.4	Connection fittings	10
1.5	Lubricants	10
2	Transport and Storing	12
2.1	Transport and Packing	12
2.2	Storing	12
3	Installation	13
3.1	Setting up	13
	Conforming Use	13
	Connection to system	14
	Oil filling	14
3.5	Electrical connections	15
4	Operation	16
4.1	Shutdown	16
5	Maintenance	17
5.1	Safety Information	17
	Maintenance Intervals	17
	Leybold Service	18
	Oil level	18
	Oil changing	18
	Exhaust filter replacement	19
5.7	Gas ballast cleaning	19
5.8	3	19
5.9	· · · · · · · · · · · · · · · · · · ·	19
	0 Fan cover cleaning	19
ວ.1′	1 Checking the oil recovery system	19
6	Problem analysis	20
7	Spare parts	22
8	Waste Disposal	26
	FIL Doctaration of Conformity	27

Safety Information

NOTICE

Obligation to Provide Information

Before installing and commissioning the pumps, carefully read these Operating Instructions and follow the information so as to ensure optimum and safe working right from the start.



The Leybold SOGEVAC® has been designed for safe and efficient operation when used properly and in accordance with these Operating Instructions. It is the responsibility of the user to carefully read and strictly observe all safety precautions described in this Section and throughout the Operating Instructions. The SOGEVAC® must only be operated in the proper condition and under the conditions described in the Operating Instructions. It must be operated and maintained by trained personnel only.

Consult local, state, and national agencies regarding specific requirements and regulations. Address any further safety, operation and/or maintenance questions to our nearest office.

DANGER indicates an imminently hazardous situation which, if not avoided, will result in death or serious injury.

DANGER



WARNING indicates a potentially hazardous situation which, if not avoided, could result in death or serious injury.

WARNING



CAUTION indicates a potentially hazardous situation which, if not avoided, could result in minor or moderate injury.

CAUTION



NOTICE is used to notify users of installation, operation, programming or maintenance information that is important, but not hazard related.

NOTICE



We reserve the right to modify the design and the specified data. The illustrations are not binding.

Retain the Operating Instructions for further use.

This Manual is valid for standard products. If the delivered pump is a special version, then the pump will be delivered with an additive document which is to be understood as a part of the Instruction Manual.

Safety Information

0 **Important Safety Information**

WARNING









0.1 **Mechanical Hazards**

Never expose part of the body to the vacuum. There is a danger of injury. Never operate the pump with an open and thus accessible inlet. Vacuum connections as well as oil filling and oil draining openings must not be opened during operation of the pump.

DANGER



Electrical Hazards 0.2

- The electrical connection must only be provided by a trained person. Please observe the national regulations in the country of use like EN 50110-1 for Europe, for example.
- 2 Disconnect the unit from the power supply before starting any work.

CAUTION



0.3 Thermal Hazards

When operating pump is hot and some surfaces could reach a temperature higher than 80 °C (176 °F). There is a risk of burn by touching.

DANGER













Hazards Caused by Materials and Substances

- SOGEVAC® pumps are **not** designed:
 - for pumping of dusty, aggressive, corrosive, flammable or explosive gases or gases mixtures;
 - for pumping of oxygen or other highly reactive gases with a greater concentration than atmospheric concentration (>20%);
 - for pumping liquids;
 - for working in flammable, explosive or dusty environment. In case of doubt, please contact Leybold.
- Depending on the process involved, dangerous substances and oil may escape from the pump. Take the necessary safety precautions!
- 3 Take appropriate precautions to insure that the pump cannot start.
- 4 If the pump has pumped hazardous gases it will be absolutely necessary to determine the nature of the hazard involved and take the appropriate safety precautions.
- 5 Observe all safety regulations!
- 6 Take adequate safety precautions prior to opening the intake or exhaust port.
- Respect the instructions concerning environment protection when discarding used oil or exhaust filters!

Safety Information

0.5 Danger of Pump Damage

closed or restricted pump exhaust.

- Liquid and solid particles must not enter the pump. Install the adequate filters, separators and/or condensers. In case of doubt consult Leybold.
 - The intake line of the pump must never be connected to a device with over atmospheric pressure. Design the exhaust line so that no pressure higher than 1,15 bar abs. (0,15 bar rel.) can occur. Never work with
- 3 Operating of the pump without oil or operating with incorrect direction of rotation can destroy the pump or lead to oil backstreaming.
- 4 Never use discarded seals. Always assemble using new seals.
- The pump must be packaged in such a way that it will not be damaged during shipping, and so that no harmful substances can escape from the package.

NOTICE



1 Description

SOGEVAC® pumps are designed for pumping of inert gases in the range of rough vacuum, between atmospheric pressure and ultimate pressure of the pump.

When removing condensable vapours, a gas ballast valve must be used.

1.1 Principle of operation

The SOGEVAC® pumps are single stage oil sealed rotary vane vacuum pumps.

The rotor, having three slots in which the vanes are sliding, is eccentrically installed in a pump cylinder (stator). The vanes separate the interior space into 3 chambers. The volume of these chambers varies with the rotation of the rotor.

The gas sucked into the inlet chamber is compressed and then pushed out at the exhaust valve.

The oil injected in the inlet chamber guarantees the air-tightness, the lubrication and cooling of the pump. It is dragged off by the compressed gases and roughly separated by gravity when entering in the oil sump. A fine separation is then operated in the exhaust filter. The proportion of oil in the exhaust gas is thus reduced below the visibility threshold (over 99% entrapment rate). The collected oil is flowing back to the generator through an internal transfer. A non-return valve is included in the oil return screw system to avoid an oil flow from the generator to the oil casing when the pump works at inlet pressures greater than 150mbar. Therefore, continuous operation above 150mbar is not recommended and can lead to oil spilling from the exhaust.

The pumps are equipped with a permanent gas ballast for pumping condensable vapors.

The anti suck back valve at the inlet flange avoids oil coming back into the inlet line when the pump is stopped, in condition that the valve is clean and in good condition.

1.2 Standard specification

The amount of oil needed for the first filling is supplied next to the pump.

The intake port is blanked off by a protective cap.

When ordering spare parts, please always state the serial and catalog numbers of the pump.


1.3 Technical characteristics

26 22.5 ≤0.5 ≤0.8	31 25 ≪0.5 ≪0.8
≤0.5	≤0.5
≪0.8	≪0.8
10	10
85	100
64	67
0.9-3000	1.1-3600
IP55 - F	IP55 - F
1X10 ⁻³	1X10 ⁻³
LVO 140 / 1	LVO 140 / 1
26(3φ)-27(1φ)	26(3φ)-27(1φ)
G 3/4 + G1/2	G 3/4 + G1/2
G 3/4	G 3/4
	85 64 0.9-3000 IP55 - F 1X10 ⁻³ LVO 140 / 1 26(3φ)-27(1φ) G 3/4 + G1/2

¹⁾ to DIN 28400 and following numbers


²⁾ operated at the ultimate pressure without gas-ballast, free-field measurement at a distance of 1 m


³⁾ with room temperature 20 to 25 $^{\circ}\text{C}$




SPACE FOR EXHAUST FILTER EXCHANGE AND COOLING


SPACE FOR THE MOTOR'S VENTILATION





Ref. No	SV25 FP	Capacitors	L max.	Н	Weight
960251 FP	3 -	0	231		26kg
960256 FP	1- 230V	C1	275	193	26kg
960261 FP	1- 115V	C1 + C2	275	235	27kg





1.4 Connection fittings

ltem	Specification	Size	Part No.
1*	Reduction + O-ring	G 3/4 M - G 1/2 F	951 24
2	Connecting piece (three piece)	G 1/2 M/F	711 18 020
3	Screw in nipple	G 1/2 M - 16KF	711 18 120
4	Centering ring	DN 16KF	183 26
5	Clamping ring	DN 16KF	183 41
6	Hose connection	DN 16KF- 25mm	711 18 300
7	Hose connection	G 1/2 M - 25mm	711 18 011
8	PVC tubing	25mm	711 18 323
9	T - piece	G 1/2 M-F-F	711 18 250
10	Vacuum control valve	G 1/2 M	951 86
11	Vacuum control valve with shut-off valve	G 1/2 M	951 87
12	Ball valve	G 1/2 M/F	711 30 113
13	Spring vacuum meter	G 1/2 M	951 92
14	Elbow 90°	G 1/2 M/F	711 18 210
15	Dust filter paper	G 1/2 M/F	951 50
15	Dust filter charcoal	G 1/2 M/F	711 27 092
15	Dust filter metal	G 1/2 M/F	711 27 093
15	Dust filter polyester	G 1/2 M/F	711 27 094
	Inlet filter element for filter pos. (15):		
	Filter element metal		E710 65 813
	Filter element polyester		712 61 280

1.5 Lubricants

The SOGEVAC SV25 FP should be run with LVO140, or an equivalent oil approved by Leybold that meets these requirements:


- ■low vapor pressure, when at high temperatures;
- ■flat viscosity curve;
- ■minimum water content and absorption;
- ■good lubricating properties; and
- ■resistant to aging under mechanical strain.

When using other oil brands, employ low doped, non detergent mineral oils of viscosity class ISO VG 32.

Using the other special-grade lubricants for specific applications is possible.

Please consult Leybold.

Only use lubricants which have been fully qualified by Leybold.



Oil LVO140	Ref.No.
1L	L14001

LVO140 is a food grade oil, H1 certificated by the NSF for incidental contact with food products.

Transport and Storing

2 Transport and Storing

2.1 Transport and packing

SOGEVAC vacuum pumps pass a rigorous operating test in our factory and are packed to avoid transport damage. Please check packing on delivery for transport damage.

Packing materials should be disposed off according to environmental laws or reused.

These operating instructions are part of the consignment.

The connection ports are blanked off by plastic protective caps or self-adhesives. Take these caps or self-adhesives away before turning on the pump.

The necessary LVO140 oil is shipped in a separate can.

Pumps which have been filled with oil must only be moved in the upright position (horizon-tally). Otherwise oil may escape. The angle of slope may not be over 10° max. Avoid any other orientations while moving the pump.

Use only lifting devices appropriated to the pump weight. Check name plate. Do not use other pump elements than the lifting lugs as handles.

CAUTION



Check the pump for the presence of any oil leaks, because there is the danger that someone may slip on the oil which has leaked from the pump.

2.2 Storing





Until the pump is put back in to service again, the pump should be stored in a dry place, preferably at room temperature (20 °C - 168 °F). Before taking the pump out of service, it should be properly disconnected from the vacuum system, purged with dry nitrogen and the oil should be exchanged too. The gas ballast must be closed and if the pump is to be shelved for a longer period of time is should be sealed in a plastic bag together with a desiccant (Silicagel).

If the pump has been shelved for over one year, standard maintenance must be done and the oil must be exchanged too before the pump is put in to service once more. We recommend that you contact the service from Oerlikon Leybold.

Installation

3 Installation

The standard pump is not suitable for installation in explosion hazard areas.

Please contact us, when you are planning such an application. Before installing the pump you must reliably disconnect it from the electrical power supply and prevent the pump from running up inadvertently.

The pump must only be installed and started by suitably qualified and trained personnel.

Observe all safety regulations.

WARNING







3.1 Setting up

The pump can be set up on any flat, horizontal surface on its rubber supports.

Under the pump are threaded bores M6 for securing the pump or screwing in vibration absorbers (extras).

The oil level cannot be read properly if the pump is tilted. The may lead to insufficient being sucked in even though the oil level glass is still covered.

The pump's ambient temperature should be between 12°C (55°F) and 40°C (104°F). By modifying the pump or changing the oil type, the pump can be run at a higher or lower ambient temperature. Please consult us about this.

To ensure adequate cooling of the pump; leave space at the air intake and exhaust points (see Fig. 1). Also ensure that there is enough space for changing the exhaust filter (see Fig. 1).

Make sure to keep the air intake of the motor clean. The pump must be kept clean (no dust deposit).

3.2 Conforming Use

SOGEVAC[®] pumps are designed for pumping of inert gases in the range of medium vacuum, between atmospheric pressure and ultimate pressure of the pump.

When removing condensable vapors, a gas ballast valve must be opened.

SOGEVAC[®] pumps are not designed for pumping of aggressive, corrosive, flammable or explosive gases. By presence of aggressive, flammable, corrosive or explosive gases, contact Oerlikon Leybold. These pumps are not designed for working in flammable or explosive environment. In case of doubt, contact Oerlikon Leybold for the ATEX pump range.

The pumps are not suitable for pumping liquids or media which contain dust. Corresponding protective measures must be introduced. In case of doubt, contact Leybold.

Installation

3.3 Connection to system

Inlet connection

The inlet flange can be connected with a vacuum-tight flexible hose and/or pipe.

The pipes should cause no stresses on the pump's flanges. If necessary, compensators must be installed.

Avoid restriction of the pipes in order not to decrease the pumping speed of the pump. The nominal diameter of the pipes has to be least the same as the diameter of pump's inlet flange.

Liquid and solid particles must not enter the pump. Install the adequate filters, separators and/or condensers. In case of doubt consult Leybold.

WARNING



The intake line of the pump must never be connected to a device with over atmospheric pressure.

Connection to exhaust side

No isolation or restricting devices should be installed in the exhaust line of the pump.

If an exhaust line is installed, it must at least have the same diameter as the exhaust flange. It should be installed in a manner so that no condensate can enter the pump (siphon, slope).

WARNING



The maximum exhaust pressure must neither exceed 1.15 bar absolute (0.15 bar relative), nor fall under atmosphere pressure minus 15 mbar corresponding pressure regulating devices to be installed by the user.

A pump exhaust to be connected if oil mist or process gases are to be avoided in the pump area.

3.4 Oil filling

The necessary oil is supplied in a can beside the pump. To fill in the oil, unscrew the oil fill plug and fill in until the oil level reaches the MAX-mark beside the oil sight glass.

NOTICE



Operating of the pump without oil or operating with incorrect direction of rotation can destroy the pump.

Installation

3.5 Electrical connection

The electrical connection must only be provided by a trained person. Please observe the national regulations in the country of use like EN 50110-1 for Europe, for example.

Disconnect the unit from the power supply before starting any work.

Voltage and frequency mentioned on the motor nameplate must agree with the supply voltage.

The drive motor must be protected against over loads according to IEC 60204-1 and IEC 61010-1.

To check the direction of rotation of pumps with three-phase motor, flick the ON/ OFF switch for a short time at atmospheric pressure. If the direction of rotation is not identical with the one indicated by the arrow sticking on the motor hood, then inverse any two of the electrical phases in the terminal box. Looking at the motor fan cover, the direction of rotation has to be counter-clockwise.

DANGER



Operation

4 Operation

CAUTION



Take note of warning labels on the pump.

Use ear protection in case of operation at high inlet pressures.

Clean eventual oil on the floor.

The pumps are equipped with a permanent gas ballast for pumping condensable vapors.

The vacuum pump must be run for 30 minutes before operating with condensable vapors with the inlet connection closed, in order to reach the operating temperature of about 75°C. Only up from this operating temperature, condensable vapors can be pumped.

NOTICE



Don't open the pump to condensable vapors until it has warmed to operating temperature; pumping process gas with a cold pump results in vapors condensing in the oil.

After use, the pump has to be left running for an additional 30 minutes with the inlet connection closed, to clear the oil of condensates.

4.2 Shutdown

The inlet flange of the SOGEVAC pumps contains an anti-suckback valve. It closes the inlet flange when the pump is voluntarily or accidentally shut down, thus maintaining the vacuum in the connected system and preventing oil from being sucked back into the system. Except the indications in chapter 4 there are no particular precautions for the shutdown of the pump. If the pump must be stopped for a longer period, see chapter 2.2.

The anti-suckback valve operates reliably only if kept in good and clean condition. It is not a safety valve.

NOTICE



When the pump has been switched off due to over heating, initiated by the motor protection, the pump must be cooled down to the ambient temperature, and must only be switched on again manually after having eliminated the cause.

Maintenance

5 **Maintenance**

5.1 Safety Information

Depending on the process involved dangerous substances may escape from the pump and oil. Take the appropriate precautions.

Observe the safety regulations.

The pump is hot and some surfaces could reach a temperature higher than 80° C (176°F). There is a risk of burn by touching.

Disconnect the power before disassembling the pump.

Make absolutely sure that the pump cannot be accidentally started.

When disposing of used oil please observe the relevant environmental regulations!

All work must be done by suitably trained personnel. Maintenance or repairs carried out incorrectly will affect the life and performance of the pump and may cause problems when filing warranty claims.

Never mount used seals; always mount new seals.

5.2 Maintenance Intervals

The intervals stated in the maintenance schedule are approximate values for normal pump operation. Unfavorable ambient conditions and/or aggressive media may significantly reduce the maintenance intervals.

Maintenance job	Frequency	Section
Oil level checking	Daily	5.4
1st oil change	After 150 h of operation	5.5
Subsequent oil changes	Every 500 to 2000 h	5.5
	(depending on application) of operation or 6 months	
Exhaust filter replacement	If oil mist at ex-haust or annually	5.6
Gas ballast valve	Monthly checking	5.7
Inlet flange sifter cleaning	6 months	5.8
Anti-suck back valve checking	6 months	5.9
Fan cover cleaning	6 months	5.10
Electrical connection checking (only by a specialist)	6 months	

To simplify the maintenance work we recommend to combine several jobs.

DANGER

















NOTICE



Maintenance

5.3 Leybold Service

Whenever you send us in equipment, indicate whether the equipment is contaminated or is free of substances which could pose a health hazard. If it is contaminated, specify exactly which substances are involved. You must use the form we have prepared for this purpose.

A copy of the form has been reproduced at the end of these Operating Instructions: "Declaration of Contamination for Compressors, Vacuum Pumps and Components". Another suitable form is available from: www.leybold.com \rightarrow Downloads \rightarrow Download Documents \rightarrow Declaration of Contamination.

Attach the form to the equipment or enclose it with the equipment.

This statement detailing the type of contamination is required to satisfy legal requirements and for the protection of our employees.

We must return to the sender any equipment which is not accompanied by a contamination statement.

CAUTION



The pump must be packaged in such a way that it will not be damaged during shipping, and so that no harmful substances can escape from the package.

5.4 Oil level

The oil level should be checked at least once a day. If the oil level is below the "MAX" mark, oil has to be added until the level reaches the mark. If the oil level is below the "MIN" mark, stop the pump and check it.

5.5 Oil changing

Oil must be changed after the first 150 operating hours. Further oil changes, depending on operating conditions (products, vapors, ambient temperature...) must be done every 500 to 2000 operating hours or at least every 6 months.

A oil quality label stuck to the pump helps user judge if oil should be changed or not.

When oil color reaches "CHANGE" shade, it is a signal to change oil. oil change frequency given by oil label is just informative, the real oil life time depends on chemical characteristics.


- If the viscosity at 25 °C exceeds 0.3 Pa s, the oil should be changed.
- The neutralization value is determined according to DIN51558. If it reaches 2, the oil should be changed.

User can decide a postponement of oil change based on their experience and professional management. In case of doubt, don't risk operation with used oil, it's preferable to replace oil.

If there is considerable pollution, it could be necessary to change the oil more frequently. Oil changing must be done with a switched off and still warm pump.

Open the oil drain plug and let run out the used oil into an appropriate container. Refasten the oil drain plug when oil runs slower, start up the pump briefly (5 sec. max) and switch off immediately. Reopen the oil drain plug and drain the rest of the oil.

Before refastening the oil drain plug, inspect the O-ring and if necessary replace it. Open the oil fill plug and pour in clean oil; refasten the oil fill plug. The pump has to be rinsed out if there is considerable pollution. Therefore pour in clean oil up to the low edge of the oil level glass, let the pump run briefly (for a few minutes) then drain the oil again.



Oil quality label

Maintenance

5.6 Exhaust filters replacement

Oil mist escaping form the exhaust during operation indicates that the filter is probably choked up. Increased motor current could also be the result of a dirty exhaust filter. Open the exhaust hood, take out the filter and replace it.

Also check the gasket of the exhaust flange and change it if necessary.

5.7 Gas ballast cleaning

If the filter of the gas ballast is dirty, the gas ballast is no longer operative. The filter has to be replaced (see spare parts list).

5.8 Inlet flange sifter cleaning

To clean the inlet flange sifter, disconnect the inlet flange and clean the sifter with blast air or an appropriate solvent.

5.9 Anti-suck back valve checking

The anti-suck back valve should be checked at the same time as the inlet flange screen and if dirty, be cleaned with an appropriate solvent. Also check, if there is no damage on the sealing part of the valve.

5.10 Fan cover cleaning

Dirt blockage of the fan cover may lead to over heating of the motor and the pump. Put off the cover and clean it with blast air. Before starting the pump again, be sure that the cover has been reassembled.

5.11 Checking the oil recovery system

When replacing the exhaust filter, check the cleanliness and the proper operation of the float valve.

After having disassembled the exhaust flange, unscrew the oil recovery screw and push the float valve by using its metallic part inside the oil casing, clean the nozzle and check that the float itself oscillates free around its axle and that the valve is tight.

Clean the float chamber of the oil casing. Reassemble in the reverse sequence.

Troubleshooting

6. Troubleshooting

Fault	Possible cause	Remedy	Reference section*
Pump does not start.	Pump is connected incorrectly. Motor protection switch incorrectly set. Operating voltage does not match motor. Motor is malfunctioning.	Connect the pump correctly. Set motor protection switch properly. Replace the motor. Replace the motor.	3.5 3.5
	Oil temperature is below 12°C (54°F).	Heat the pump and pump oil or use different oil.	1.5
	Oil is too viscous. Exhaust filter / exhaust line is clogged.	Use appropriate oil grade. Replace the filter or clean the exhaust line.	5.5 5.6
Pump does not	External leak .	Repair the pump.	-
reach ultimate oressure.	Float valve does not close.	Repair the valve.	5.11
	Anti-suckback valve is malfunctioning.	Repair the valve.	5.9
	Inadequate lubrication due to : ■ unsuitable or contaminated oil, ■ clogged oil filter, ■ clogged oil lines.	Change the oil (degas it, if necessary). Replace the oil filter. Clean the oil casing.	5.5 5.5
	Vacuum lines are dirty.	Clean vacuum lines.	
	Pump is too small.	Check the process date ; replace the pump, if necessary.	
Pumping speed is too low.	Dirt trap in the intake port is clogged.	Clean the dirt trap. Precaution : install a dust filter in intake line.	5.8
	Exhaust filter is clogged. Connecting lines are too narrow or too long.	Install new filter elements. Use adequately wide and short connecting lines.	5.6 3.3
After switching off	System has a leak.	Check the system.	
pump under vacu- um, pressure in system rises too fast.	Anti-suckback is malfunctioning.	Repair the valve.	5.9
Pump gets too hot.	Cooling air supply is obstructed.	Set pump up correctly.	3.1
	Cooler is dirty.	Clean the cooler.	
	Ambient temperature is too high.	Set pump up correctly.	3.1
	Process gas is too hot.	Change the process.	-
	Oil level is too low.	Add oil to reach the correct oil level.	5.4
	Oil is unsuitable.	Change the oil.	5.5
	Oil cycle is obstructed.	Clean or repair the oil lines.	
	Exhaust filter / exhaust line is obstructed.	Replace the exhaust filter, clean the exhaust line.	5.6

Troubleshooting

Fault	Possible cause	Remedy	Reference section*
Oil in intake line or	Oil comes from the vacuum system.	Check the vacuum system.	
in vacuum vessel.	Anti-suckback valve is obstructed.	Clean or repair the valve.	5.9
	Sealing surfaces or anti-suckback valve are damaged or dirty.	Clean or repair the intake port and valve.	5.9
	Oil level is too high.	Drain the excess oil.	5.5
Pump's oil con-	Exhaust filters are clogged or damaged.	Replace the filters.	5.6
sumption too high, oil mist at exhaust.	Nozzle of float valve is clogged.	Check the valve, clean the nozzle.	5.11
on mot at exhaust.	Oil level is too high.	Drain the excess oil.	5.5
Oil is turbid.	Condensation.	Degas the oil or change the oil and clean the pump.	4
		Precaution: open the gas ballast valve or insert a condensate trap.	
		Clean the gas ballast intake filter.	5.7
Pump is excessive- ly noisy.	Oil level is very low (oil is no longer visible).	Add oil.	5.4

^{*} Reference section: This coluum refers to the section in the Operating Instructions that contains the applicable repair information.

Never mount used seals. Always mount new seals.

7 Spare parts


To guarantee safe operation of the Leybold pump, only original spare parts and accessories should be used. When ordering spare parts and accessories, always state pump type and serial number. You can find part numbers in the spare parts list.

Consumables and main spare parts kits for SOGEVAC® pumps are usually available on stock at Leybold's service centers. The list of these parts is given here after and in the spare parts table where the contents of each kits is detailed.

- Exhaust demisters
- LVO140 Oil (Special oils please refer to the specific notice of the pump or contact Leybold).
- Service kit
- Set of seals
- Repair kit

We recommend to use these kits which have been defined to allow an optimal maintenance or repair. individual spare parts may need longer delivery time.

Repairs requiring the replacement of the stator or the rear endplate should be made by the Leybold Service.



1 3 Screw CHC Ms x 10 Q8.8	Pos.	Qty	Specification	Dimensions (mm), material	Ref, no.	Notes			
3	1	3	Screw	CHC M6 x 10 Q8.8					
3 1 End plate without GB 971422950 3 1 Fan end plate with GB 71421710	2	10	Screw	CHC M6 x 16 Q8.8					
3	3	1	End plate with GB		971422940	Incl. 4,5			
3 1 Fan end plate W/O GB 971446770	3	1	End plate without GB		971422950				
4 1 GB screw kit 71418070	3	1	Fan end plate with GB		71421710	Incl. 4,5			
5 1 GB silencer 71418060 ● 6 1 Rotor 71416310 ● 7 3 Vane set of 3 71416290 ● 8 2 Screw CHC M8 x 60 Q8.8 ● 9 4 Washer W8 ● 10 2 O-ring 93 FKM 71237720 ● 11 2 O-ring 6,02 X 2,62 FKM 71237720 ● 12 1 Pump cylinder Consult Leybold Service 12 1 Pump cylinder Consult Leybold Service 13 2 Rubber mount D20x15 M6 71418020 15 1 Supporting plate 71414030 16 1 Rubber mount D20x15 M6 71414030 17 1 Motor 1PH 0,9/1,1KW 230V 50/60Hz Incl. 17a,c,d,18,19,20,21,22,23 17c 1 Terminal box 971422800 971422800 17c 1 Terminal box 971423060	3	1	Fan end plate W/O GB		971446770				
6 1 Rotor 71416310 7 3 Vane set of 3 71416290 8 2 Screw CHC M8 x 60 Q8.8 9 4 Washer W8 10 2 O-ring 93 FKM 71237720	4	1	GB screw kit		71418070		•		
7 3	5	1	GB silencer		71418060			•	
8 2 Screw CHC M8 x 60 Q8.8 9 4 Washer W8 10 2 O-ring 93 FKM 71237720 ● 11 2 O-ring 6.02 X 2,62 FKM 71237600 ● 12 1 Pump cylinder Consult Leybold Service 13 2 Rubber mount D20x15 M6 71418020 15 1 Supporting plate 71416240 16 1 Rubber mount D20x15 M6 71414030 17 1 Motor 1PH 0,9/1,1KW 230V 50/60Hz Incl. 17a,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 40μF 971423050 17c 1 Terminal box 971423090 17 1 Motor 1ph 0,9/1,1KW 100V 50/60Hz Incl.17a,b,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 97142300 17b 1 Capacitor 110μF 97142300 17c 1 Terminal box 971423130 17d 1 Terminal box 971422830 17d 1 Terminal box 971422830 17d 1 Terminal box 971422830 17d 1 Terminal box 971423000 17d 1 Terminal box 971423130 17d 1 Terminal box 971423130 17d 1 Terminal box 971423300 17d 1 Terminal box 97142330 17d 1 Terminal box 971423300	6	1	Rotor		71416310				
9 4 Washer W8 10 2 O-ring 93 FKM 71237720 ● 11 2 O-ling 6.02 X 2,62 FKM 71237600 ● 12 1 Pump cylinder 13 2 Rubber mount D20x15 M6 71418020 □ 15 1 Supporting plate 71416240 16 1 Rubber mount D20x15 M6 71414030 □ 17 1 Motor 1PH 0,9/1,1KW 230V 50/60Hz Incl. 17a,c,d,18,19,20,21,22,23 Consult Leybold Service □ 17a 1 Capacitor 40μF 971423050 □ 17b 1 Terminal box 971422800 □ 17c 1 Terminal box 971423090 □ 17b 1 Capacitor 110μF 971423060 □ 17c 1 Terminal box 971423080 □ 17d 1 Terminal box 97142300 □ 17d 1 Terminal box 97142300 □ 17e 1 Terminal box 971423	7	3	Vane set of 3		71416290			•	
10 2 O-ring 93 FKM 71237720 ■	8	2	Screw	CHC M8 x 60 Q8.8					
11 2 O-ring 6.02 X 2.62 FKM 71237600	9	4	Washer	W8					
11 2 O-ring 6,02 X 2,62 FKM 71237600 12 1 Pump cylinder 13 2 Rubber mount D20x15 M6 71418020 15 1 Supporting plate 16 1 Rubber mount D20x15 M6 71414030 17 1 Motor 1PH 0,9/1,1KW 230V 50/60Hz Incl. 17a,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 40µF 971423050 17c 1 Terminal box 971423090 17 1 Motor 1ph 0,9/1,1KW 100V 50/60Hz Incl. 17a,b,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110µF 971423060 17b 1 Capacitor 110µF 971423060 17c 1 Terminal box 971423130 17d 1 Terminal box 971423130 17d 1 Terminal box 97142300 17e 1 Capacitor 110µF 97142300 17e 1 Capacitor 97142300 17e 1 Terminal box 971423130 17e 1 Capacitor 97142300 17e 1 Terminal box 97142300	10	2	O-ring	93 FKM	71237720		•		
12	11	2		6,02 X 2,62 FKM	71237600		•		
13 2 Rubber mount D20x15 M6 71418020	12	1				Consult Leybold Service			
15				D20x15 M6	71418020				
16 1 Rubber mount D20x15 M6 71414030 17 1 Motor 1PH 0,9/1,1KW 230V 50/60Hz Incl. 17a,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 40μF 971423050 17c 1 Terminal box 971423090 17 1 Motor 1ph 0,9/1,1KW 100V 50/60Hz Incl.17a,b,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 110μF 971423060 17c 1 Terminal box 971423060 17c 1 Terminal box 971423330 17d 1 Terminal board 97142830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 110μF 971423060 17c 1 Terminal box 971423300 17c 1 Terminal box 971423060 17d 1 Terminal box 971423070 17d 1 Terminal box 971423070 17d 1 Terminal box 97142300 17d 1 Terminal box 97142300 17d 1 Terminal box 97142830 17d 1 Terminal box 97142300 17d 1 Terminal box 971423000				Danie me					
17				D20x15 M6					
Consult Leybold Service 17a					71414000	Incl. 17a c d 18 19 20 21 22 23			
17a 1 Capacitor 40μF 971423050 17c 1 Terminal box 971422800 17d 1 Terminal board 971423090 17 1 Motor 1ph 0,9/1,1KW 100V 50/60Hz Incl.17a,b,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 110μF 97142330 17c 1 Terminal box 971422830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 0,9/1,1KW 230/400V 50/60Hz 230/460V 60Hz 220V 50/60Hz 220V 50/60Hz 20V	17	'	MOTOL II II	0,9/1,11(00 250 0 50/00112					
17c 1 Terminal box 971422800 17d 1 Terminal board 971423090 17 1 Motor 1ph 0,9/1,1KW 100V 50/60Hz Incl.17a,b,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 110μF 971423130 17c 1 Terminal box 971422830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 0,9/1,1KW 230/400V 50/60Hz 230/460V 60Hz 230/460V 60Hz 220/V 50/60Hz Incl.17C,d,18,19,20,21,22,23 Consult Leybold Service 17c 1 Terminal board 97142380 Incl.17C,d,18,19,20,21,22,23 Consult Leybold Service 17c 1 Terminal board 971	172	1	Canacitor	40uE	071/23050	Consult Leybold Service			
17d 1 Terminal board 971423090 17 1 Motor 1ph 0,9/1,1KW 100V 50/60Hz Incl.17a,b,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 110μF 971423060 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 97142300 17c 1 Terminal board 971422830 17d 1 Terminal board 97142380 17d 1 Terminal box 97142380 17d 1 Terminal box 97142360 17d 1 Terminal box 97142360 17d 1 Terminal box 971423540 Set of seals FKM 71419490				40μι					
17 1 Motor 1ph 0,9/1,1KW 100V 50/60Hz Incl.17a,b,c,d,18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 110μF 971423060 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 0,9/1,1KW 230/400V 50/60Hz 230/460V 60Hz 2230/460V 60Hz 200V 50/60Hz 17c 1 Terminal box 97142340 17d 1 Terminal box 97142340 Repair kit 971423100									
Consult Leybold Service 17a				0.0/4.4/2/M.400//.50/0011=	97 1423090	Incl. 47- h - 4 40 40 20 24 22 22			
17b 1 Capacitor 110μF 971423060 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 9714223130 17d 1 Terminal board 971422830 17 1 Motor 3PH 0,9/1,1KW 230/400V 50/60Hz 2230/460V 60Hz 230/460V 60Hz 200V 50/60Hz Incl.17C,d,18,19,20,21,22,23 Consult Leybold Service 17c 1 Terminal box 971423080 17d 1 Terminal board 971423540 Set of seals FKM 71419490	17	1	Motor 1pn	0,9/1,1KW 100V 50/60HZ					
17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 50/60Hz 230/460V 50/60Hz 200V 50/60Hz 17 1 Terminal box 971423540 17 1 Terminal board 971423540 Set of seals FKM 71419490	_17a	1	Capacitor	110µF	971423060				
17d 1 Terminal board 971422830 17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 20,91,1KW 230,400V 50,60Hz 230,460V 60Hz 200V 50,60Hz 17c 1 Terminal box 971423080 17d 1 Terminal box 971423540 Set of seals FKM 71419490	17b	1	Capacitor	110μF	971423060				
17 1 Motor 1PH 1,1KW 115V 60Hz Incl.17a,b,c,d, 18,19,20,21,22,23 Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 50/60Hz Incl.17C,d,18,19,20,21,22,23 Consult Leybold Service 17c 1 Terminal box 971423080 17d 1 Terminal box 971423080 17d 1 Terminal box 971423540 Set of seals FKM 71419490	17c	1	Terminal box		971423130				
Consult Leybold Service 17a 1 Capacitor 110μF 971423060 17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 50/60Hz 2 230/460V 60Hz 200V 50/60Hz Incl.17C,d,18,19,20,21,22,23 Consult Leybold Service 17c 1 Terminal box 971423080 17d 1 Terminal board 971423540 Set of seals FKM 71419490	17d	1	Terminal board		971422830				
17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 50/60Hz 230/460V 60Hz 200V 50/60Hz 17c 1 Terminal box 971423080 17d 1 Terminal box 971423540 Set of seals FKM 71419490	17	1	Motor 1PH	1,1KW 115V 60Hz					
17b 1 Capacitor 60μF 971423070 17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 50/60Hz 230/460V 60Hz 200V 50/60Hz 17c 1 Terminal box 971423080 17d 1 Terminal box 971423540 Set of seals FKM 71419490	17a	1	Capacitor	110µF	971423060				
17c 1 Terminal box 971423130 17d 1 Terminal board 971422830 17 1 Motor 3PH 50/60Hz 230/460V 60Hz 200V 50/60Hz Incl.17C,d,18,19,20,21,22,23 Consult Leybold Service 17c 1 Terminal box 971423080 17d 1 Terminal board 971423540 Set of seals FKM 71419490	17b	1			971423070				
17d 1 Terminal board 971422830 17 1 Motor 3PH 0,9/1,1KW 230/400V 50/60Hz 2230/460V 60Hz 2230/460V 60Hz 2200V 50/60Hz Incl.17C,d,18,19,20,21,22,23 Consult Leybold Service 17c 1 Terminal box 971423080 17d 1 Terminal board 971423540 Set of seals FKM 71419490 Repair kit 971423100	17c	1	•						
17 1 Motor 3PH		1	Terminal board						
17c 1 Terminal box 971423080 17d 1 Terminal board 971423540 Set of seals FKM 71419490 Repair kit 971423100				50/60Hz 230/460V 60Hz					
17d 1 Terminal board 971423540 Set of seals FKM 71419490 Repair kit 971423100	17c	1	Terminal box		971423080		_		
Set of seals FKM 71419490 Repair kit 971423100	17d	1	Terminal board				Î		
Repair kit 971423100				FKM				•	
Service kit 971423450								<u></u>	↑
			Service kit		971423450				

Pos.	Qty	Specification	Dimensions (mm), material	Ref, no.	Notes			
18	1	Fan		71422750				
19	1	Fan cover		71422760				
20	1	Key	6X30	71416300				
21	1	Ball bearing			Consult Leybold Service			
22	1	Radial shaft seal	FKM		Consult Leybold Service	•		
23	1	End bearing plate			Consult Leybold Service			
24	1	Inlet spring		71415640				
25	1	Anti suckback valve		71042990		•		
26	4	O-ring	34.52,FKM	71419340		•		
27	1	Inlet adapter		71413110				
28	1	Dirt trap		71413440				
29	1	Intake flange	G 3/4	71416170				
29	1	Intake flange	NPT 3/4	71418080				
30	4	Screw	CHC M6 x 35 Q8.8					
31	1	O-ring	28,FKM	71217590		•		
32	1	Reduction + o-ring	G 3/4-G 1/2	95124	Incl.31			
32	1	Reduction	NPT 3/4- NPT 1/2	71422140				
33	1	Valve plate		71418570			•	
34	1	Valve stop		71418580			•	
35	2	Centering pin	D3.5X10					
36	1	Washer	WZ6					
37	2	Nut	HM8 Q6					
38	1	Flat gasket		71419730		•		
39	1	Grid		71416180				
40	2	O-ring	27 X 2.5,FKM	71217580		•		•
41	2	Plug , slotted	HC G 3/4	71256380	Incl.40			
42a	1	Exhaust flange	G 3/4	71416220				
42b	1	Exhaust flange	NPT 3/4	71418090				
43	1	Spring unit		71420370			•	•
44	1	Exhaust filter		EK6520369			•	•
45	1	Flat gasket		971423480		•		•
46	1	Oil return screw		71420720	Incl.47			
47	1	O-ring	8X2,FKM	71217650		•		
48	1	Oil level glass	3/4	71219480		•		
49	1	Float compl.		71417210	Incl.49a,b			
49a	1	O-ring	8X2,FKM	71217650		•		
49b	1	Oil return valve seal		71212500		•		
50	1	Oil casing		71421730	Incl.50a			
50a	2	Locking screw	M8-25/15J=12 Q6.8					
51	1	Lifting lug	M8	71402970				
52	2	Plug + o-ring	G 1 1/4	71420140	Incl.26			
60	1	Radial shaft seal	DN18x35x7	71419180		•		
61	1	Fan hub		71422030				
62	1	Fan		71419190				
63	1	Nut	M8					
64	1	Screw	HC M8x50					
65	1	Cover		71420250	Incl.66			
66	3	Screw	HC M6x12			A		
67	2	Screw	CHC M6x8 Q8.8					
		Set of seals	FKM	71419490			•	
								
		Repair kit		971423100				
		Service kit		971423450				_

Disposal

Contamination

8 Waste Disposal

The equipment may have been contaminated by the process or by environmental influences. In this case the equipment must be decontaminated in accordance with the relevant regulations. We offer this service at fixed prices. Further details are available on request.

WARNING



Contaminated parts can be detrimental to health and environment. Before beginning with any work, first find out whether any parts are contaminated. Adhere to the relevant regulations and take the necessary precautions when handling contaminated parts.

Separate clean components according to their materials, and dispose of these accordingly. We offer this service. Further details are available on request.

When sending us any equipment, observe the regulations given in Section "5.3 Leybold service".

Disposal of Waste Oil

Owners of waste oil are entirely self-responsible for proper disposal of this waste.

Waste oil from vacuum pumps must not be mixed with other substances or materials.

Waste oil from vacuum pumps (Leybold oils which are based on mineral oils) which are subject to normal wear and which are contaminated due to the influence of oxygen in the air, high temperatures or mechanical wear must be disposed of through the locally available waste oil disposal system.

Waste oil from vacuum pumps which is contaminated with other substances must be marked and stored in such a way that the type of contamination is apparent. This waste must be disposed of as special waste.

European, national and regional regulations concerning waste disposal need to be observed. Waste must only be transported and disposed of by an approved waste disposal vendor.





EU Declaration of Conformity

(Translation of original Declaration of Conformity)

The manufacturer:

Leybold Equipment (Tianjin) Co., Ltd.

No.8 Shuangchenxi Rd.

Beichen Economic Development Area (BEDA)

Tianjin, 300400, PR China

herewith declares that the products specified and listed below which we have placed on the market, comply with the applicable EU Council Directives. This declaration becomes invalid if modifications are made to the product without agreement of Leybold.

Product designation:

SOGEVAC

Type:

SV10B, SV16B, SV25B, SV40B, SV65B, SV100B, SV200, SV300B,

SV630B(F), SV750B(F), SV10FP, SV16FP, SV25FP, SV45FP, SV70FP, SV105FP, SV200FP and SV300FP, and their variants,

excepted pumps delivered without motor

The products complies to the following European Council Directives:

Machinery Directive (2006/42/EC)

The safety objectives of the Low Voltage Directive 2014/35/EU were complied with in accordance with Appendix 1 No. 1.5.1 of Machinery Directive 2006/42/EC.

Electromagnetic Compatibility (2014/30/EU)

RoHS Directive (2011/65/EU) & (2015/863/EU)

The following harmonized standards have been applied:

EN 1012-2:1996+A1:2009 Compressors and vacuum pumps — Safety requirements — Part 2:

Vacuum pumps

EN 60204-1:2006/A1:2009 Safety of machinery — Electrical equipment of machines — Part 1:

General requirements

EN 61000-6-2:2005/AC:2005 Electromagnetic compatibility (EMC) - Part 6-2: Generic standards -

Immunity for industrial environments

EN 61000-6-4:2007/A1:2011 Electromagnetic compatibility (EMC) - Part 6-4: Generic standards -

Emission standard for industrial environments

Documentation officer:

Herbert Etges

Leybold GmbH, Bonner Str. 498, D-50968 Köln

T: +49(0)221 347 0 F: +49(0)221 347 1250 documentation@leybold.com

Cologne, April 26, 2017

Cologne, April 26, 2017

ppa. Andries Desiron

VP Engineering

Industrial Vacuum Division

i.A. Ernst Schnacke

Head of Quality Assurance Methods

& Technical Standards

Notes



Declaration of Contamination of Compressors, Vacuum Pumps and Components

The repair and / or servicing of compressors, vacuum pumps and components will be carried out only if a correctly completed declaration has been submitted. Non-completion will result in delay. The manufacturer can refuse to accept any equipment without a declaration. A separate declaration has to be completed for each single component.

THE R. P. LEWIS CO., LANSING, MICH.							1.6. 1 1 66
This declaration	may be come	nated and	aaned	only by	authorized	andio	ttets halfilei II
TITIO ACCIDITATION	THAY BO OUT &	notou anu			- authorize u	and c	adamica stant.

Qustomer/Dep./Institute:		Reason for retur	Reason for return: 🔀 applicable please mark		
Address:		Repair:		able warranty	
		Exchange:			
				ranged / received	
Person to contact:		<u>Return only:</u>	rent	loan for credit	
Phone:	Fax:	_ Calibration:	□DKD	Factory-calibr.	
End user:		_ Quality tes	st certificate	DIN 55350-18-4.2.1	
0 Passerintian of the Levihald product	Failure de	a animbia n			
A. Description of the Leybold product:	<u>Failure de</u>	scription:			
Material description:		l t -			
Catalog number:		•			
	Applicatio				
Type of oil (ForeVacuum-Pumps) :	Аррисацо	n- Process:			
B. Condition of the equipment	No ¹ Yes No		<u>imination :</u>	<u>No^ŋ Yes</u>	
1. Has the equipment been used		to xic			
Drained (Product/service fluid)	<u></u>	comosi		님 님	
3. All openings sealed airtight	▼ 	flamma		님 님	
4. <u>Purqed</u>		explos			
If yes, which deaning agent			ctive ²⁾		
and which method of cleaning			iological ²⁾		
¹⁾ If an swered with "No", go to D. ←		other h	narmful substa	inces 🔲 📙	
What substances have come into c Trade name and / or chemical term of According to safety data sheet (e.g. to X Tradename:	service fluids and substances proces oxic, inflammable, como sive, radioactiv		ubstances		
X Iradename:	Glernical name				
b)					
c)					
[d)			<u> </u>		
Are these substances harmful? Dangerous decomposition product: If yes, which?	No Ye	+			
2) Components contaminated by microl evidence of decontamination.	biological, explosive or radioactive	products/substances	will not be a	ccepted without written	
or acres or accontantination.					
D. <u>Legally binding declaration</u>	n supplied on this form is accurate:	and sufficient to judge	e any contam	ination level.	
D. <u>Legally binding declaration</u> I/ we hereby declare that the information	n supplied on this form is accurate :	and sufficient to judgo	e any contam	nination level.	
D. <u>Legally binding declaration</u> I/ we hereby declare that the information Name of authorized person (block letters):	n supplied on this form is accurate :	and sufficient to judgo	e any contan	nination level.	

Notes

Notes

Sales and Service

Germany

Leybold GmbH

Sales, Service, Support Center (3SC) Bonner Strasse 498 D-50968 Cologne T: +49-(0)221-347 1234 +49-(0)221-347 31234 sales@leybold.com www.leybold.com

Leybold GmbH

Sales Area North Branch Office Berlin Industriestrasse 10b D-12099 Berlin

+49-(0)30-435 609 0 +49-(0)30-435 609 10 sales.bn@leybold.com

Leybold GmbH Sales Office South Branch Office Munich

Karl-Hammerschmidt-Strasse 34 D-85609 Aschheim-Dornach +49-(0)89-357 33 9-10 +49-(0)89-357 33 9-33 sales.mn@leybold.com service.mn@leybold.com

Leybold Dresden GmbH Service Competence Center Zur Wetterwarte 50, Haus 304 D-01109 Dresden

Service: +49-(0)351-88 55 00 +49-(0)351-88 55 041 info.dr@leybold.com

Europe

Belgium

Levbold Nederland B.V. Belgisch bijkantoor

Leuvensesteenweg 542-9A B-1930 Zaventem Sales:

+32-2-711 00 83 +32-2-720 83 38 sales.zv@leybold.com

+32-2-711 00 82 +32-2-720 83 38 service.zv@leybold.com

Leybold France S.A.S.

Leybold France S.A.S.
Parc du Technopolis, Bâtiment Beta
3, Avenue du Canada
F-91940 Les Ulis cedex
Sales and Service:
T: +33-1-69 82 48 00
F: +33-1-69 07 57 38 info.ctb@leybold.com sales.ctb@leybold.com

Leybold France S.A.S.

Valence Factory 640, Rue A. Bergès B.P. 107

F-26501 Bourg-lès-Valence Cedex T: +33-4-75 82 33 00 F: +33-4-75 82 92 69 marketing.vc@leybold.com

Great Britain

Leybold UK LTD.

Unit 9

Silverglade Business Park Leatherhead Road Chessington Surrey (London) KT9 2QL Sales: +44-13-7273 7300 +44-13-7273 7301 sales.In@leybold.com Service: +44-13-7273 7320 +44-13-7273 7303

service.In@leybold.com

Leybold Italia S.r.l.

Via Filippo Brunelleschi 2 I-20093 Cologno Monzese T:+39-02-27 22 31 F: +39-02-27 20 96 41 sales.mi@leybold.com Service:

T:+39-02-27 22 31 F: +39-02-27 22 32 17 service.mi@leybold.com

Netherlands

Leybold Nederland B.V.

Floridadreef 102 NL-3565 AM Utrecht Sales and Service +31-(30) 242 63 30 F: +31-(30) 242 63 31 sales.ut@leybold.com service.ut@leybold.com

Switzerland

Leybold Schweiz AG, Pfäffikon

Hinterbergstrasse 56 CH-6312 Steinhausen Warehouse and shipping address: Riedthofstrasse 214 CH-8105 Regensdorf Sales: +41-44-308 40 50

+41-44-302 43 73 sales.zh@leybold.com Service: +41-44-308 40 62 +41-44-308 40 60

service.zh@leybold.com

Spain

Leybold Spain, S.A. C/. Huelva, 7 E-08940 Cornellà de Llobregat (Barcelona) Sales

+34-93-666 43 11 +34-93-666 43 70 sales.ba@leybold.com Service:

+34-93-666 46 11 +34-93-685 43 70 service.ba@leybold.com

America

HSA

Leybold USA Inc.

5700 Mellon Road USA-Export, PA 15632 +1-724-327-5700 +1-724-325-3577 info.ex@leybold.com Sales:

+1-724-327-5700 +1-724-333-1217

Service:

+1-724-327-5700 +1-724-325-3577

Brazil

Levbold do Brasil

Rod. Vice-Prefeito Hermenegildo Tonolli, No. 4413 - 6B Distrito Industrial Jundiaí - SP CEP 13.213-086 Sales and Service: T: +55 11 3395 3180 F: +55 11 99467 5934 sales.ju@leybold.com service.ju@leybold.com

Asia

P. R. China

Leybold (Tianjin) International Trade Co. Ltd.

Beichen Economic Development Area (BEDA), No. 8 Western Shuangchen Road Tianjin 300400 China

Sales and Service: +86-400 038 8989 +86-800 818 0033 +86-22-2697 4061 F: +86-22-2697 2017 sales.tj@leybold.com service.tj@leybold.com

India

Leybold India Pvt Ltd. T-97/2, MIDC Bhosari

Pune-411 026 Indien Sales and Service +91-80-2783 9925 +91-80-2783 9926 sales.bgl@leybold.com service.bgl@leybold.com

Japan

Leybold Japan Co., Ltd.

Headquarter Shin-Yokohama A.K.Bldg., 4th Floor 3-23-3, Shin-Yokohama Kohoku-ku, Yokohama-shi Kanagawa 222-0033 .lanan Sales: +81-45-471-3330 +81-45-471-3323

Leybold Japan Co., Ltd.

sales.yh@leybold.com

Tsukuba Technical Service Center 1959, Kami-yokoba Tsukuba-shi, Ibaraki-shi 305-0854 Japan

Service T: +81-29 839 5480 F: +81-29 839 5485 service.iik@leybold.com

Malaysia

Leybold Malaysia **Leybold Singapore Pte Ltd.** No. 1 Jalan Hi-Tech 2/6

Kulim Hi-Tech Park Kulim Kedah Darul Aman 09000 Malaysia Sales and Service: +604 4020 222 +604 4020 221 sales.ku@leybold.com service.ku@leybold.com

South Korea

Leybold Korea Ltd.

3F. Jellzone 2 Tower Jeongja-dong 159-4 Bundang-gu Sungnam-si Gyeonggi-do Bundang 463-384, Korea Sales: T: +82-31 785 1367 F: +82-31 785 1359 sales.bd@leybold.com Service:

623-7, Upsung-Dong Cheonan-Si Chungcheongnam-Do Korea 330-290 +82-41 589 3035 +82-41 588 0166 service.cn@leybold.com

Singapore

Leybold Singapore Pte Ltd.

42 Loyang Drive Loyang Industrial Estate Singapore 508962 Singapore Sales and Service: +65-6303 7030 +65-6773 0039 sales.sg@leybold.com service.sg@leybold.com

Taiwan

Leybold Taiwan Ltd.

10F.,No. 32, Chenggong 12th St., Zhubei City, Hsinchu Country 302 Taiwan, R.O.C. Sales and Service: T: +886-3-500 1688 +886-3-583 3999 sales.hc@leybold.com service.hc@leybold.com

Headquarter Leybold GmbH

Bonner Strasse 498 D-50968 Koeln T:+49-(0)221-347 0 F:+49-(0)221-347 1250 info@leybold.com

